ONLINE CERTIFICATIONS DIRECTORY

XCFR2.E60678
Terminal Blocks - Component

Page Bottom

Terminal Blocks - Component

See General Information for Terminal Blocks - Component

WIELAND ELECTRIC GMBH E60678
BRENNERSTRASSE 10-14
96052 BAMBERG, GERMANY

Cat. No.	Wire Range	Wire Type	FW	TQ Lb In.	V	A	UG	CA
7572L4/30B,	26-6	Cu	1	20.5	15,300,	65,10,	C,D	2(105),4
					300	65	B	
7572L2/20B,								
7572L2/30B								
7572L2/5/30B	22-6	Cu	1	20.5	600	65	C,D	2(105)
8190, 8390, 8190E	22-12	Cu	2	7	300	15	C	2(105)
by one or two								
digit number.								
99.211.1320.5	22-12	Cu	2	8	300	10	C	2(85),*
LPST1/2 thru 20, LPSTL1/2 thru 20	22-14	Cu	2	4	300	5	B,C	2(105)
BKM6/35	14-2	Cu	1	27	1000	115	B,C	2(105),4,#
BKM8/35	14-1/0	Cu	1	54	1000	150	B,C	2(105),4,#
BKM10/35	10-250	Cu	1	90	1000	255	B,C	2(105),4,#
BKM12/35	10-250	Cu	1	90	1000	255	B,C	2(105),4,#
9060Si5x20KR	10-16	Cu	2	8	300	10	C	2(130)*
KL58 followed by	#	Cu	2	#	250	40	B,C	2(105)*
/3,/5,/6,								
followed by /1								
KL58 followed by /3,/4,	8-14	Cu	1/2	22	250	40	B,C	2(105)*
/5,/6,followed by S								
or SWA, maybe followed								
by R, maybe								
followed by /1,								
may be followed by SL.								
may be followed by GW								
Note: Note: # 8-14 sol/str at 22lb-in torque, 10 max sol/str at 18 lb-in torque.								
WKB2.5/U	12-22	Cu	2	7	300	20	B,C,D	2(105)*
ST29/10BC,-/10BL, -/10S	14-22	Cu	2	7	300	+	D	2(105)*

WKB2.5/ST/U,-/B/U	12-22	Cu	2	7	300	+	B,D	2(105)*
WKB2.5/STB2/U-16,	12-22	Cu	2	7	30	1	D	2(105)*
WKB2.5/STB2/U-20, WKB2.5/STB4/U-34,								
WKB2.5/STB4/U-40								
Z5.599.9025, Z5.599.9125	—	—	2	—	300	+	B,D	2(85)*
Note: (+) 5 amps per terminal with all terminals carrying Current, 10A if one terminal is carrying Current.								
8375 may be followed by	10-22+	Cu	2	7	300	30#	B,D	2(105)*
/02 thru /12, followed by /7.5								
8375 may be followed by	10-22+	Cu	2	7	600	30#	B,C,D	2(105)*
/02 thru /12, followed by /10								
Note: # Max 35A for factory-wiring only.								
Note: + Wire range extended to min 30 AWG sol/str for factory wiring only.								
8185, 8285, 8385, 8485	12-22+	Cu	2	—	300	20#	B,D	2(105)
followed by TOPV or TOPH, with or without,								
ZP8385 TOPN or ZP8485 TOPN,								
with or without AP8185 TOPN,								
with or without BZ8185 TOPN								
Note: # Max 35A for factory-wiring only.								
Note: + Wire range extended to min 30 AWG sol/str for factory wiring only.								
8158, 8258, 8358, 8458	12-30	Cu	2	—	300	20	B,D	2(105),4
may be followed by /02 thru /24,								
followed by TOPV or TOPH,								
with or without OB								
9700(1)	12-18	Cu	2	8	600	20	C	2(105),*
9700(2)	12-18	Cu	2	8	600(3)	20	C	2(105),*
9220A(2)	12-18	Cu	2	8	600(3)	20	C	2(105),*
9700B/5	12-18	Cu	2	8	600	20(4)	C	2(105),*
9700B/6	18-10	Cu	2	8	600	30	C	2(105),*
9700B/6US	18-10	Cu	2	8	600	30	C	2(105),*
RFK1/95(5)	3/0-6	Cu	2	89	600	200	C	2(105),*
RFK1/150(5)	300-1/0 (2) 3	Cu	2	133	600	275	C	2(105),*
RFK1/185(5)	400-1/0	Cu	1	177	600	325	C	2(105),5,*
RFK1/240(5)	500-1/0 (2) 250 (2) 3	Cu	1/2	177	600	375	C	2(105),*
Note: (1) May be followed by suffix B, followed by /6TKSD.								
Note: (2) May be followed by suffix B, followed by /6TKS, followed by P1, P2, or P3.								
Note: (3) 300V max with suffix P1, P2, or P3.								
Note: (4) 30A max for factory-wiring.								

Note: (5) Followed by F, FK, FM, FMK, K, PA or S35.

KK1.5/S15	12-22	Cu	2	8	300	20	C	2(105),*
KK1.5/M/S15	12-22	Cu	2	8	300	20	C	2(105),*
KK2.5	12-22	Cu	2	8	600	20	C	2(105),*
WK2.5(1)	22-12	Cu	2	5.5	600	20	C	2(105),*
WK4(1)	22-10#	Cu	2	8	600	30	C	2(105),*
WK4TKS(5)	22-10	Cu	2	8	300	10	C	2(105),*
WK4/U(6)	22-10#,@	Cu	2	8	300	30	C	2(105),*
WK4/U(6)	22-10#	Cu	2	8	300	30	C	2(105),*
WK4/D(7)	22-10	Cu	2	6	600	30	C	2(105),*
WK4TKSD/U	22-10	Cu	2	8	300	25	C	2(105),*
WK4TKG(8)	22-10	Cu	2	8	300	10	C	2(105),*
LEG 396 41	22-10	Cu	2	8	300	10	C	2(105),*
WK4TKM(8)	22-10	Cu	2	8	600	20	C	2(105),*
WK6(1)	22-8##	Cu	2	11	600	50	C	2(105),*
WK10(1)	16-6###	Cu	2	35	600	65	C	2(105),*
WK16(1)	12-4	Cu	2	35	600	85	C	2(105),*
WK35(1)	10-2	Cu	2	50	600	95	C	2(105),*
WK70(1)	6-2/0	Cu	2	150	600	175	C	2(105),*
WKI10(2)	16-6	Cu	2	35	600	65	C	2(105),*
WKI16(2)	12-4	Cu	2	35	600	85	C	2(105),*
WKI35(2)	2-10	Cu	2	50	600	95	C	2(105),4
WK2.5/U(/D)8113S/H(9)	22-12	Cu	2	5.5	300	20	C	2(105),*
WK2.5/U(/D)8113S/V(4)	22-12	Cu	2	5.5	300	15	C	2(105),*

Note: #May be used with 2 No. 16, 2 No. 18, 3 No. 20 or 3 No. 22.

Note: ##Cat. No. WK6/U may be used with 2 No. 12, 2 No. 16, 3 No. 18 or 3 No. 22.

Note: ###Cat. No. WK10 may be used with 2 No. 12, 2 No. 14, or 3 No. 16.

Note: @May be used with 2 No. 14, Sol/STR AWG when both conductors are of the same type.

WKN10(3)	16-6	Cu	2	18	600	65	C	2(105),*
WKN16(3)	12-4	Cu	2	22	600	85	C	2(105),*
WKN35/35(9)	10-2	Cu	2	36	600	95	C	2(105),*
WKN35/(3)(11)(12)	10-1/0	Cu	2	36	600	150	C	2(105),*
WKN70(3)	6-2/0	Cu	2	150	600	175	C	2(105),*,4
WKN150(3)	2/0-400	Cu	2	89	600	335	C	2(105),*,4
WKI 35 SL/35(9)	2-10	Cu	1	50	—	—	—	2(105)
WKN70 SL/U	6-2/0	Cu	1	150	—	—	—	2(105)
WK4 SL/U	22-10	Cu	1	8	—	—	—	2(105)

Note: (1) May be followed by suffix SL, followed by /32, /35, or /U; may be followed by VO.

Note: (2) Followed by SL/35 or /U; may be followed by VO.

Note: (3) With or without suffix SL, followed by suffix /U; may be followed by VO.

Note: (4) May be followed by /LED25, /LED50 or /VK; may be followed by VO.

Note: (5) Followed by /U, D/U, P1/U, P2/U or P3/U; may be followed by VO.

Note: (6) Followed by F1 or F2; may be followed by VO.

Note: (7) Followed by suffix 1/2, 2/2, 2/2 SL or E, followed by /U; may be followed by VO.

Note: (8) Followed by Suffix /U, P1/U, P2/U or P3/U, may be followed by Suffix -DIST-D or -DIST-1N4007 or -SiST or -TRST, may be followed by Suffix GL or LED; may be followed by VO.

Note: (9)May be followed by VO.

Note: (10) Cat. No. WK4SL/U has been evaluated for its suitability as a protective conductor terminal block and complies with the applicable grounding requirements for terminals for use in a protective cirCuit.

Note: (11) Jumper bar Cat. No. IVB WKN 35-2, have been evaluated together with terminal block WKN 35/U. Temperature test was conducted on two pole version with the maximum Current of 95A for this terminal blocks. The suitability of these Jumper bars in other combinations shall be determined in the end-use equipment.

Note: (12) WKN35/U may be used with 2 AWG4 and WKN35/35 with 2 AWG10.

WKFN 2.5, followed by E/P, or E/VB/F/P, or 2P/2F, or F/P/F, or E, F, P	24-12	Cu	2	—	500	20	C	2(105),4
WKFN 2.5, followed by 2P/2F/SL, or F/P/F/SL, or E/F/P/SL	24-12	Cu	2	—	—	—	C	2(105),4
8113, 8213, 8313, 8413(1)(2)(5)	12-30	Cu	2	4-5.5	300	15	B,D	2(105),*
8313, 8413 (4)	12-22	Cu	2	4-5.5	600	15	B,D	2(105),*
8113 SU(3)	12-22	Cu	2	0.8	300	12	B,D	2(105),*

Note: (1) Component Terminal Blocks - Cat. Nos. 8113, 8213, 8313, 8413, followed by B, BL, may be followed by C, followed by 2 thru 24, or /2/4 thru /12/24 or /3/2 thru /23/12,may be followed by VR, VL, TOP, TOP LED, SH, or TOP K, may be followed by F, M, A or F2, may be followed by OB, may be followed by GR, SW, GN, or any other two digit color designation, may be followed by TR, AU, and/or THR.

Note: (2) Component Terminal Block Headers - Cat. Nos. 8113, 8213, 8313, 8413, followed by S, or SE, may be followed by C, followed by 2 thru 24, or /2/4 thru /12/24 or /3/2 thru /23/12, followed by G, W, OL, OR, S, S1, DFWW, DFLS, TOP, or TOP K, may be followed by F, OF, M, F2 and or A, may be followed by OB, may be followed by GR, SW, GN, or any other two digit color designation, may be followed by AU or THR.

Note: (3) Cat. Nos. 8113 followed by SU is suitable with header Type 8213 BL.

Note: (4) each second pin is omitted.

Note: (5) Cat. No. 8113 B/.. VR... is suitable for carrying two wires of wire range AWG 30-16 sol./str. (double wire connection) of the same size in one clamping cage.

8113, 8213, 8313, 8413 (3)	12-22	Cu	2	—	300	12	B,D	2(105),*

Note: (3) Component Terminal Blocks - Cat. Nos. 8113, 8213, 8313, 8413, w/suffix BFK or BFKE and Headers w/suffix SUFK.

8113, 8213 (4)	12-22	Cu	2	—	600	15	B,D	2(105),*

Note: (4) Component Terminal Blocks - Cat. Nos. 8113/ 8213 B or S, /3/2 through /23/12, and 8113/8213 BL w/suffix TR.

8243SEG/2/4..24/48W0B, 8213SEG/2/14..24/48G0B, 8113SEG/2/4..24/48G0B	24-16	Cu	1	—	300	15	B,D	2(105)
7572L4/2 OB	26-6	Cu	1	20.5	150,300,300	65,10,65	C,D,B	2(105),4
7572L2/3/2 OB	22-6	Cu	1	20.5	600	65	C,D	2(105)
7573L2/1.3.4 WOB	22-8	Cu	1/2	20.5	300	10	C	2(105),4
	26-8	Cu	1	20.5	300	10	C	2(105),4
8113SEG/2..24/4..48 WOB,	24-16	Cu	1	—	300	15	B,D	2(105)
8113SEG/2..24/4..48 GOB								
8213B/2..24 SOB	22-12	Cu	2	4.5	300	15	B,D	2(105),4
	(2)14, str							

	only							
	(2)16, str only							
	(2)18, str only							
8213SEG12..24/4..48 WOB,	24-16	Cu	1	—	300	15	B,D	2(105)
8213SEG12..24/4..48 GOB								
7386/2..8 TOP H OB,	22-10	Cu	1/2	5.5	300,300	30	B,D	2(105),
8486/2..4 TOP H OB, 8486/2..4 TOP V OB	26-10	Cu	1	5.5	300,300	30	B,D	2(105)
8142(1)	21-12	Cu	2	6.0	600	13	B,C,D	2(105),*
8543(1)	22-16	Cu	2	3.0	300	10	B,C,D	2(105),*
Note: (1) Followed by /one or two digit number or suffix /4/2-/24/12 incl., with or without suffix OB, followed by Z5.530. followed by 32 thru 53 followed by 25 or followed by Z5.530. followed by 62 thru 71 followed by 25 or followed by Z5.531. followed by 02 thru 23 followed by 25 or followed by Z5.531. followed by 32 thru 53 followed by 25 or Z5.531. followed by 62 thru 71 followed by 25 or Z5.531. followed by 82 thru 91 followed by 25 or Z5.532. followed by 02 thru 23 followed by 25 or followed by Z5.532. followed by 32 thru 53 followed by 25 or Z5.532. followed by 62 thru 71 followed by 25 or Z5.532. followed by 82 thru 91 followed by 25.								
WK4/THSi(2)	22-10	Cu	2	7.0	600	15	C	2(105),*
WK10/SIU(1)	6-22	Cu	2	35	600	15	C	2(105),*
WK10/SIUD(3)	6-22	Cu	2	35	600	50	C	2(105)
Note: (1) Followed by 5x20, 5x25, 5x30 or 6.3x32 (1/4 x 1-1/4) with or without suffix GLB or NGL, may be followed by /VO.								
Note: (2) Followed by 5 or 6.3, may be followed by GL or LED, may be followed by 12, 24, 60, 250, 500, followed by /U; may be followed by VO.								
Note: (3) May be followed by VO.								
8276	14-30	Cu	2	7.0	300	23	B,C,D	2(120),*
8276-TKS	14-30	Cu	2	7.0	300	15	B,C,D	2(120),*
8276-Si-D	14-30	Cu	2	7.0	300	6.3	B,C,D	2(120),*
8135, 8235, 8335, 8435, 8491 (1)	12-22	Cu	2	7.0	300 %	30+	B,D	2(110),*
8291, 8391, 8491, 8191 (1)	12-22	Cu	2	7.0	300%	30+	B,D	2(110)*
	(2) No. 18, Sol.,							
	(2) No. 18 Str.							
8191 (4)	12-22	Cu	2	7.0	300%	30+	B,D	2(110)*
	(2) No. 18, Sol.,							
	(2) No. 18 Str.							
8191R, 8291R (3)	12-22	Cu	2	5-7	300%	30+	B,D	2(110),
8191R/R2, 8291R/R2	12-22	Cu	2	5-0	300	28	B,D	2(105)
8234(2)	14-30	Cu	2	5.0	300	20+++	B,D	2(110),*
8593, 8893(2)	16-30	Cu	2	2.7	300	10	B,D	2(110),*
8134, 8192, 8292(2)	14-30	Cu	2	5.0	300	16++	B,D	2(110),*
8195(1)	**	Cu	2	5.0	300%	10	B,D	2(110),*
Note: (1) Each may be followed by suffix D, E or V, followed by 2/4-12/24 inclusive or 2/6-12/36 inclusive or 2/8-12/48 inclusive or 3/2-23/12 inclusive or one or two digit number, may be followed by Suffix Z, ZW, ZN, ZF, with or without Suffix OB.								

Note: (2) Followed by a one or two digit number, may be followed by suffix Z, ZN or ZW, GW with or without suffix OB, with or without suffix MS, with or without suffix THT.								
Note: (3)Followed by one or two digit number or 3/2-23/12 inclusive, may be followed by Suffix PM, may be followed by suffix Z with or without OB, may be followed by GW.								
Note: (4) Followed by one digit number 2 or 3, may be followed by suffix WVR or WVL, with suffix OB, may be followed by two digit color code.								
Note: (+) All types (except 8234) are rated 20 amp max for field-wiring and 30 amp max for factory-wiring.								
Note: (+++) Type 8234 is rated for 15 amp max for field-wiring and 20 amp max for factory-wiring. Refer to Spacing Table in report for limitations.								
Note: %Voltage is increased to 600V when terminal in every other pole is removed.								
Note: (**) Nos. 30-14 AWG for the upper tiers and Nos. 20-12 AWG for the lowest tier.								
Note: (++) 16 amp max. factory, 15 amp max field-wiring. Refer to Spacing Table in report for limitations.								
8191 FK	12-28	Cu	—	—	300	15, 10	B,D	2(110)
8291 EFK, 8291 DFK	12-28	Cu	—	—	300	10	D	2(110)
4E/GW	14-20	Cu	2	4	250(1)	15(3)	C	2(105),*
4E/DS/GW	16-22	Cu	2	4	250(1)	10	C	2(105),*
6E/GW (2)	12-22	Cu	2	5	300(1)	20	C	2(105),*
6E/DS/GW, 6EH/GW	14-22	Cu	2	5	300(1)	15	C	2(105),*
10E/GW (2)	10-22	Cu	2	7	300(1)	30(4)	C	2(105),*
10E/DS/GW	12-22	Cu	2	7	300(1)	20	C	2(105),*
16E/GW (2)	8-22	Cu	2	11	300(1)	50	C	2(105),*
16E/DS/GW	10-22	Cu	2	11	300(1)	30	C	2(105),*
20E/GW (2)	4-20	Cu	2	18	300(1)	70	C	2(105),*
20E/DS/GW	6-22	Cu	2	18	300(1)	65	C	2(105),*
Note: (1) 600v when terminal strips are used.								
Note: (2) Followed by 1-12 incl.								
(3) Suitable 20A for factory-wiring.								
(4) Suitable 40A for factory-wiring.								
KL16(1)	12-22	Cu	2	5	250	20	B	2(75),*
Note: (1) Followed by 4, 6, 8, 12, 16 or 20, followed by PA or PA DS.								
9700A/5S35	18-12	Cu	2	8.0	600	30	B,C	2(105),*
9700A/6S35	18-10	Cu	2	8.0	600	30	B,C	2(105),*
9700A/8S35(1)	18-8	Cu	2	10(2)	600	50	B,C	2(105),*
9700A/10S35(1)	18-6	Cu	2	18.0	600	70	B,C	2(105),*
9700A/12S35US	18-4	Cu	2	30.0	600	100	B,C	2(105),*
9700A/12S35	14-4	Cu	2	35.0	600	100	B,C	2(105),*
Note: (1) May be followed by suffix US.								
Note: (2) When provided with suffix US-8.0 lb-in.								
9700/16, 9700B/16, 9700A/16S35(1)	12-2(2)	Cu	2	50.0	600	130	B,C	2(105),*
Note: (1) May be followed by suffix US.								
Note: (2) Cat. No. 9700A/16S35 may be used with 2 No. 4 AWG Wires.								
WK4E(1)	22-10	Cu	2	6.0	300	10	D	2(105),*
WK4E/U(2)	22-10#	Cu	2	6.0	300	20	B, D	2(105),4

WK4E/U/VB(1)	22-10#	Cu	2	6.0	300	20	D	2(105),*
WK4/15(1)	22-10	Cu	2	6.0	600	10	D	2(105),*
WK4/15SL(1)	22-10	Cu	2	6.0	600	10	D	2(105),*
WKM2.5/15(1)	22-14	Cu	2	6.0	300	10	D	2(105),*
WKM4SL/15(1)	22-14	Cu	2	6.0	300	10	D	2(105),*
WK4E/SL/U(1)	22-12	Cu	2	8.0	—	—	D	2(105),*
WKN2.5E/U(1)	22-12	Cu	2	7.0	600	20(1)	C	2(105),*
WKN2.5E/U/VB(1)	22-12	Cu	2	7.0	600	20(1)	C	2(105),*
WKM4/15(1)	22-10	Cu	2	6.0	600	30	D	2(105),*
Note: (1) May be followed by VO								
Note: (2) May be followed by RO or OR, /LD+PO24, /LED+PO 24LD, /LD-PO24, /LD 42, /NGL, /G2, /G2/I, /GU, /GO, /G-URL or /G-ULR								
Note: # May be used with 2 No. 16, Sol/STR AWG when both conductors are of the same type								
ASG1(1)	16-12(2)	Cu	1	11.0	300	20	B,D	2(105),5,*
Note: (1) Followed by /3, /4, /5, may be followed by suffix A.								
Note: (2) Wire combinations of 3 - 5, no intermixing.								
WK(1)	18-8	Cu	1	20.0	N/A	N/A	N/A	2(105),*,5
WK(2)	18-6	Cu	1	35.0	N/A	N/A	N/A	2(105),*,5
Note: (1) Followed by /3S, /4S, /5S, /3-6S, /4-8S, /5-10S, may be followed by /IW, may be followed by /U.								
Note: (2) Followed by /3, /4, /5, may be followed by S, may be followed by -6S, -8S, -10S, /U.								
WK4(1)	22-12	Cu	2	4.0	300	10	B,D	2(105),*
WK4(2)	18-8	Cu	2	20.0	N/A	N/A	N/A	2(105),*
Note: (1) Followed by /3, or /5, may be followed by S or S2.8, may be followed by -6S, followed by /1K, followed by /IW, may be followed by U.								
Note: (2) Followed by /3, or /5, may be followed by S or S2.8, may be followed by -6S, followed by SKO, followed by /1K, may be followed by U.								
9700-B/6SL(1)	18-10	Cu	2	20.0	N/A	N/A	N/A	2(105),*
9700-B/8SL(1)	18-8	Cu	2	20.0	N/A	N/A	N/A	2(105),*
9700-B/10SL(1)	18-6	Cu	2	35.0	N/A	N/A	N/A	2(105),*
Note: (1) May be followed by suffix US.								
DST(LF)85/(1)	30-14	Cu	2	3	300	6	B,D	2(120),4
Note: (1) Followed by one or two-digit number, with or without OB.								
WKF2.5	22-12	Cu	2	N/A	600	(+)	B,C	2(110),4
WKF2.5/D(1)	22-12	Cu	2	N/A	600	(+)	B,C	2(110)
leg 396 42	22-12	Cu	2	N/A	600	(+)	B,C	2(110)
WKF2.5/M,	22-12	Cu	2	N/A	600	20	B,C	2(105)
WKF2.5/MD								
WKF4(1), WKF4-D	22-10	Cu	2	N/A	600	30	B,C	2(125),*
leg 396 04/14	22-10	Cu	2	N/A	600	30	B,C	2(125),*
leg 396 24	22-10	Cu	2	N/A	600	30	B,C	2(125),*
WKF4 NT/35	22-12	Cu	2	N/A	600	20	B,C	2(125),4#
WKF4 TKM/35	22-10	Cu	2	N/A	600	20	C,D	2(125),4

WKF6(1)	24-8	Cu	2	N/A	600	40	B,C	2(110),#1
leg 396 05/15	24-8	Cu	2	N/A	600	40	B,C	2(110),#1
leg 396 25	24-8	Cu	2	N/A	600	40	B,C	2(110),#1
WKF10(1)	24-6	Cu	2	N/A	600	55	B,C	2(110),#1
leg 396 06/16	24-6	Cu	2	N/A	600	55	B,C	2(110),#1
leg 396 29	24-6	Cu	2	N/A	600	55	B,C	2(110),#1
WKF16(1)	24-4	Cu	2	N/A	600	75	B,C	2(110),#1
WKF16(4)	24-4	Cu	2	N/A	600	75	B,C	2(110),4
leg 396 07/17	24-4	Cu	2	N/A	600	75	B,C	2(110),#1
WKF6SL(1)	24-8	Cu	2	N/A	—	—	—	2(110),#1
WKF10SL(1)	24-6	Cu	2	N/A	—	—	—	2(110),#1
leg 396 26	24-6	Cu	2	N/A	—	—	—	2(110),#1
WKF16SL(1)	24-4	Cu	2	N/A	—	—	—	2(110),#1
WKF 4 E (2)	22-10	Cu	2	N/A	600(3)	30(3)	B,C,D	2(105),#1
leg 396 36/46	22-10	Cu	2	N/A	600	30	B,C,D	2(105)
Leg 39666	22-10	Cu	2	N/A	—	—	—	2(105),#1
Note: (+) 30 amps factory only, 20 amps field and factory.								
Note: (1) May be followed by 1/2, 2/2 or /D, with or without SL, followed by /35, may be followed by BL or SW. When provided with suffix SL, there is no assigned voltage or Current rating.								
Note: (2) may be followed by /VB, /D, /SL, followed by 35, may be followed by 1D/2G OR, 1D/2G RO, G2, GO, GU, G-URL, G-ULR, LD+PO24, LD-PO24 or NGL. When provided with suffix SL, there is no assigned voltage or Current rating.								
Note: (3)- Final voltage and Current rating limited by type of disconnect used (e.g., diode and glow lamp).								
Note: (4)- followed by /35 followed by PV may be followed by /WKF, /WKC, /WKFN.								
8152N, 8252N(2)	24-14	Cu	2	N/A	300	15(1)	B,C,D	2(120),*
Note: (1): 16 Amp for factory-wiring only.								
Note: (2): Followed by /02 thru /12 incl., may be followed by suffix NH, with or without suffix OB, may be followed by two letters.								
WKF1.5E/35(1)	30-14	2	Cu	N/A	300	B,C	15	2(110),4
					600	D		
Note: (1): may be followed by BL or any two character designation.								
WKF4 TKG/35 (3)	22-12	Cu	2	N/A	600(4)	1	B,C	2(110),*
LEG 396 40	22-12	Cu	2	N/A	600(4)	1	B,C	2(110),*
Note: (3) Type-SIST, may be followed LED or GL; or Type-DIST, may be followed by 1N4007-1, 1N4007-2, or D.								
Note: (4)- Final Current and voltage rating by type of disconnect used (e.g. fuse or diode).								
8813B/, 8813BS/(1)	16-30	Cu	2	2.7	300	8	B,D	2(65),*
Note: (1) Followed by a one or two digit number, with or without Suffix VL or VR, with or without Suffix F, with or without OB.								
8813S/(2)	NA	NA	1	NA	300	8	B,D	2(65),*
Note: (2) Followed by a one or two digit number, may be followed by suffix G or W, with or without suffix F.								
WK2.5-4KOI(1)	12-22	Cu	2	7	300	20	B,D	2(105),*
WK2.5-4KI(2)	12-22	Cu	2	8	300	25	B,C	2(105),*
WK2.5-3D(2)	12-22	Cu	2	8	300	25	B,C	2(105),*
Note: (1) Followed by /U, may be followed by suffix NGN or PGN.								

Note: (2) Followed by /U, may be followed by suffix NGN or PGN. When provided with suffix "SL" this device is provided with a grounding terminal in the lower tier which has no assigned voltage or Current rating.								
WEG(1)	10-22	Cu	2	7	600	—	C	2(105),4,*2
Note: (1) May be followed by /N, followed by 4A, 6A or 8A, may be followed by /0.								
8105 (1)	12-26	Cu	2	7	300	10	B,D	2(110),4,#
Note: (1) Followed by B, BU, FU or BF, may be followed by G, followed by /2-7 or 3/1 up to and inclusive 23/4, may be followed by CO-C99, may be followed by VL, VLA, VR, VRA, VB-SL or VB-N/SL, may be followed by OB.								
8520 (1)	20-24 solid	Cu	2	—	300	4	B,D	2(105),4
Note: (1) Followed by B, BL or S, followed by /2 through /24 inclusive, or /3/2 through /23/12, may be followed by G, W, G 0.8 or G 1.0, may be followed by OB.								
WKC1(2)	30-18	Cu	2	N/A	600	13	B,D	2(105),4
WKC1 TKG DIST or DIST-D	30-18	Cu	2	N/A	600	10	B,D	2(105),4#
WKC1 TKG DIST-1N4007-1, -2	30-18	Cu	2	N/A	600	1	B,D	2(105),4#
WKC1 SIST	30-18	Cu	2	N/A	600	6.3	B,D	2(105),4#
WKC1 SIST-LED	30-18	Cu	2	N/A	24	6.3	B,D	2(105),4#
WKC1 SIST-GL	30-18	Cu	2	N/A	230	6.3	B,D	2(105),4#
WKC2.5(2)	18-14	Cu	2	N/A	600	22	B,C,D	2(105),4
WKC2.5 TKG DIST or DIST-D	18-14	Cu	2	N/A	600	10	B,D	2(105),4#
WKC2.5 TKG DIST-1N4007-1, -2	18-14	Cu	2	N/A	600	1	B,D	2(105),4#
WKC2.5 SIST	18-14	Cu	2	N/A	600	6.3	B,D	2(105),4#
WKC2.5 SIST-LED	18-14	Cu	2	N/A	24	6.3	B,D	2(105),4#
WKC2.5 SIST-GL	18-14	Cu	2	N/A	230	6.3	B,D	2(105),4#
WKC 2.5 E /35 (3)	18-14	Cu	2	N/A	600	22	B,C,D	2(105),4#
Note: #Indicates disconnect blocks have not been evaluated for Current interruption.								
Note: (2) When provided with suffix "SL" this device is provided with a grounding terminal in the lower tier which has no assigned voltage or Current rating.								
Note: (3) f/b /1D/2G, G2, GO, GU, G-URL, LD+P024, LD-P024, NGL, OR or RO.								
8513B(1)	#16-30,	Cu	2	2.7	300	8	D	2(65)4
	(2)20,							
	(2)22							
8513 SUFK(2)	#16-30	Cu	2	—	300	8	D	2(65)4
8513 BFK(1)	#16-30	Cu	2	—	300	8	B, D	2(65)4
8513 SU/(2)	16-24	Cu	1	2.7	300	8	B	2(65)4
8513S(2)	NA	NA	1	NA	300	8	D	2(65)
Note: (1) Followed by a one or two digit number 2 through 24 inclusive or 3/12 through 23/12 inclusive, with or without Suffix F or TOP, with or without Suffix OB, may be followed by SW, GN, or any other two digit color code, may be followed by THR.								
Note: (2) followed by a one or two digit number, may be followed by Suffix G or W, with or without Suffix F, with or without suffix OB, may be followed by SW, GN, or any other two digit color code, may be followed by THR.								
Note: #Indicates wire range extended to No. 14 Sol and Str for factory wiring applications.								
8513 SEG, followed by 2/4 up to 20/40, followed by W, may be followed by OB.	NA	NA	1	NA	300	8	B, D	2(140)
8292 FK/...	28-12	Cu	2	N/A	150	15	C	2(105),4
8292 EFK/...	28-12	Cu	2	N/A	150	15	C	2(105),4

8292 DFK/...	28-12	Cu	2	N/A	150	15	C	2(105),4
WKIF 2.5 D	22-12	Cu	2	—	600	20	B,C,D	2(105),4
WKIF 2.5, followed by D-D, N-D or NT-D	22-12	Cu	2	—	300	20	B,C,D	2(105),4#
WKF 1.5 D1/2/35	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 1.5 D1/2/35 BLAU	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 1.5 D1/2SL/35	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 1.5 D2/2/35	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 1.5 D2/2/35 BLAU	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 1.5 D2/2SL/35	26-14	Cu	2	N/A	—	—	B,C	2(105)
WKF 1.5 E2/35	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 1.5 E/VB/35	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 1.5 E/SL/35	26-14	Cu	2	N/A	—	—	B/C	2(105)
WKF 1.5 SL/35	26-14	Cu	2	N/A	—	—	B/C	2(105)
WKF 1.5 /35	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 1.5 /35 BLAU	26-14	Cu	2	N/A	300	15	B,C	2(105)
WKF 35 /35	14-2	Cu	2	N/A	600	115	B,C	2(105),4
WKF 35 /35 BLAU	14-2	Cu	2	N/A	600	115	B,C	2(105),4
WKF 35 /SL/35	14-2	Cu	2	N/A	N/A	N/A	B,C	2(105),4
WKFN 2.5 /35, WKFN 2.5 D1/2/35, WKFN 2.5 D2/2/35, WKFN 2.5 D/D/35, WKFN 2.5 E3/VB/35, WKFN 2.5 E/VB/35, WKFN 2.5 E1/2/VB/35	22-12 Sol/Str	Cu	2	N/A	600	20	B, C	2(120),4
WKFN 2.5 TKM E2/35, WKFN 2.5 TKM/35, WKFN 2.5 TKM 1/2/35, WKFN 2.5 TKM 2/2/35, WKFN 2.5 TKM E1/35	24-12Sol/Str	Cu	2	N/A	300	19	B, C	2(115),4
WKFN 2.5 E1/2/N/D/35,	22-12 Sol/Str	Cu	2	N/A	300	20	B, C	2(120),4
WKFN 2.5 E/N/D/35,								
WKFN 2.5 E/N/SL/35 (#1),								
WKFN 2.5 E/D/SL/35 (#1),								
WKFN 2.5 E3/D/D/SL/35 (#1),								
WKFN 2.5 E3/N/D/SL/35 (#1),								
WKFN 2.5 E3/VB/SL/35 (#1),								
WKFN 2.5 E1/2/N/SL/35 (#1),								
WKFN 2.5 E1/2/D/SL/35 (#1)								
WKFN 2.5 E1/2/N/D/35,	22-12 Sol/Str	Cu	2	N/A	600	5	D	2(120),4
WKFN 2.5 E/N/D/35,								
WKFN 2.5 E/N/SL/35 (#1),								
WKFN 2.5 E/D/SL/35 (#1),								
WKFN 2.5 E3/D/D/SL/35 (#1),								
WKFN 2.5 E3/N/D/SL/35 (#1),								
WKFN 2.5 E3/VB/SL/35 (#1),								

WKFN 2.5 E1/2/N/SL/35 (#1),								
WKFN 2.5 E1/2/D/SL/35 (#1)								
Note: (1): Followed by suffix RO, OR, 1D/2G RO, 1D/2G OR, GU, GO, G2, G-URL, G-ULR, LD-P024, LD+P024 or NGL.								
WKFN 2.5 E3/35, WKFN 2.5 E1/2/35	22-12	Cu	2	N/A	300	20	B, C	2(120),4
WKFN 2.5 /SL/35,	22-12	Cu	2	N/A	—	—	—	2(120),4,#1
WKFN 2.5 D1/2/SL/35,								
WKFN 2.5 D2/2/SL/35,								
WKFN 2.5 E/SL/35,								
WKFN 2.5 E1/2/SL/35,								
WKFN 2.5 E3/SL/35								
WKFN 2.5 E/35	22-12	Cu	2	N/A	600	20	B, C, D	2(120),4
WKFN 2.5 E/35 (1)	22-12	Cu	2	N/A	600	20	B, C, D	2(105),4,#
WKFN 4 /35,	24-10, sol/str	Cu	2	N/A	600	30	B,C	2(105),4
WKFN 4 D1/2/35,								
WKFN 4 D2/2/35,								
WKFN 4 D/D/35,								
WKFN 4 E/VB/35								
WKFN 4 E/35 (1),	24-10, sol/str	Cu	2	N/A	300	30	B,C	2(105),4#
WKFN 4 E/N/D/35,								
WKFN 4 E/N/SL/35,								
WKFN 4 E/D/SL/35								
WKFN 4 E/35 (1),	24-10, sol/str	Cu	2	N/A	600	5	D	2(105),4 #
WKFN 4 E/N/D/35,								
WKFN 4 E/N/SL/35,								
WKFN 4 E/D/SL/35								
WKFN 4 SL/35,	24-10, sol/str	Cu	2	N/A	—	—	—	2(105),4 #1
WKFN 4 D1/2/SL/35,								
WKFN 4 D2/2/SL/35,								
WKFN 4 E/SL/35								
WKFN 4 TKG/35	24-10, sol/str	Cu	2	N/A	See note ##	See note ##	B, C, D	2(105),4
Note: (1) Followed by suffix RO, OR, 1D/2G RO, 1D/2G OR, GU, GO, G2, G-URL, G-ULR, LD-P024, LD+P024 or NGL.								

Note: ## Ampere and Voltage ratings depend on the type of fuse holder or disconnect used as specified below
Type THSI 5x20 (600V, 6.3A)
Type THSI 5x20 LED 24 (24V, 6.3A)
Type THSI 5x20 LED 60 (60V, 6.3A)
Type THSI 5x20 GL 250 (250V, 6.3A)
Type THSI 6.3x32 (600V, 10A)
Type THSI 6.3x32 LED 24 (24V, 10A)
Type THSI 6.3x32 LED 60 (60V, 10A)
Type THSI 6.3x32 GL 250 (250V, 10A)
Type THSI 6.3x32 GL 500 (600V, 10A)

Type THSI 0.5x52 GL 300 (600V, 10A)
Type SIST-.../V0 (300V, 10A)
Type SIST-LED/V0 (300V, 10A)
Type SIST-GL/V0 (300V, 10A)
Type DIST-.../V0 (600V, 10A)
Type DIST-1N4007-1/V0 (600V, 1A)
Type DIST-D/V0 (600V, 10A)
Type DIST-1N4007-2/V0 (600V, 1A)

WKC 1, may be f/b D2 or E, f/b F, may be f/b 2C or C, f/b /35. (1),(2)	24-18 SOL 24-12 STR	Cu	2	N/A	600	13	B, C	(105),4
WKC 1, followed by /SL	22-18 sol/str	Cu	2	—	—	—	—	(105),4
WKC 2.5, may be f/b D2 or E, f/b F, may be f/b 2C or C, f/b /35. (2),(3)	24-18 SOL 24-12 STR	Cu	2	N/A	600	20	B, C	(105),4
WKC 2.5, followed by /SL	18-14 sol/str	Cu	2	—	—	—	—	(105),4
Note: (1) Wire range for Piercing 22-18 SOL/STR.								
Note: (2) When provided with suffix "SL" this device is provided with a grounding terminal in the lower tier which has no assigned voltage or Current rating.								
Note: (3) Wire range for Piercing 18-14 SOL/STR.								
8562 N/3/2, 8562 N/6	16-20(**)	Cu	2	—	300	15	B	2(105),4*
8562 N	16-20(**)	Cu	2	—	300	2	B,D	2(105),4*
7415 B followed by /2 thru /8, (1)	22-10	Cu	2	5.5	600	15	B, C	2(105),4
7413 S followed /2 thru /8	—	—	—	—	600	—	—	2(105)
Note: (1) Terminal block type 7415 B shall be used with header type 7413 S only								
WKF 1.5 E/8113/35	22-14	Cu	2	N/A	300	12	B,C	2(105),4
WKF 2.5 D2/8113/35	22-12	Cu	2	N/A	300	12	B,C	2(105),4
8113 BFK/ followed by 3, 6 or 10 followed by TOPK.	22-12	Cu	2	N/A	300	12	B,C	2(105),4
8181/ DS HW	14-22	Cu	2	4	300	16	B/C	2(105),4*
WKF 4 3-D/SL/35	28-10	Cu	2	N/A	(#)	(##)	B,C	2(105),4
8474 / 2 HW, 8474 / 3 HW, 8474 / 4 HW, 8474 / 5 HW,8474 / 6 HW, 8474 / 7 HW, 8474 / 8 HW, 8474 / 9 HW,8474 / 10 HW, 8474 / 11 HW, 8474 / 12 HW, 8474 / 13 HW, 8474 / 14 HW, 8474 / 15 HW, 8474 / 16 HW, 8474 / 17 HW,8474 / 18 HW, 8474 / 19 HW, 8474 / 20 HW, 8474 / 21 HW, 8474 / 22 HW, 8474 / 23 HW, 8474 / 24 HW	10-24	Cu	2	5.5	300	30	B/D	2(105),4*
WKFN 6 (A)	24-8	Cu	2	—	600	50	B,C	2(105),4
WKFN 10 (A)	16-6	Cu	2	—	600	60	B,C	2(105),4
WKFN 16 (A)	16-4	Cu	2	—	600	85	B,C	2(105),4
Note: (A) May be followed by D1/2 may be followed by /SL followed by /35 may be followed by blue, may be followed by /PX.								
8813 S/(3)	—	—	Cu	2	—	300	—	B, D
Note: (3) followed by 2 thru 16, followed by G, GF, W. GF, may be followed by 3.2, followed by OB, FB, followed by THR.								
8513 BS/ 2 OB HW, 8513 BS/ 3 OB HW, 8513 BS/ 4 OB HW, 8513 BS/ 5 OB HW, 8513 BS/	24-16	Cu	2	—	150	8	B, D	2(105)

6 OB HW, 8513 BS/ 7 OB HW, 8513 BS/ 8 OB HW, 8513 BS/ 9 OB HW, 8513 BS/ 10 OB HW, 8513 BS/ 11 OB HW, 8513 BS/ 12 OB HW, 8513 BS/ 13 OB HW, 8513 BS/ 14 OB HW, 8513 BS/ 15 OB HW, 8513 BS/ 16 OB HW, 8513 BS/ 17 OB HW, 8513 BS/ 18 OB HW, 8513 BS/ 19 OB HW, 8513 BS/ 20 OB HW, 8513 BS/ 2 F2 OB HW, 8513 BS/ 3 F2 OB HW, 8513 BS/ 4 F2 OB HW, 8513 BS/ 5 F2 OB HW, 8513 BS/ 6 F2 OB HW, 8513 BS/ 7 F2 OB HW, 8513 BS/ 8 F2 OB HW, 8513 BS/ 9 F2 OB HW, 8513 BS/ 10 F2 OB HW, 8513 BS/ 11 F2 OB HW, 8513 BS/ 12 F2 OB HW, 8513 BS/ 13 F2 OB HW, 8513 BS/ 14 F2 OB HW, 8513 BS/ 15 F2 OB HW, 8513 BS/ 16 F2 OB HW								
8142Z / 2F2, 8142Z / 3F2, 8142Z / 4F2, 8142Z / 5F2, 8142Z / 6F2, 8142Z / 7F2, 8142Z / 8F2, 8142Z / 9F2, 8142Z / 10F2, 8142Z / 11F2, 8142Z / 12F2, 8142Z / 2F2 OB, 8142Z / 3F2 OB, 8142Z / 4F2 OB8142Z / 5F2 OB, 8142Z / 6F2 OB, 8142Z / 7F2 OB, 8142Z / 8F2 OB,8142Z / 9F2 OB, 8142Z / 10F2 OB, 8142Z / 11F2 OB, 8142Z / 12F2 OB	26-14	Cu	2	2.0	300	15(1)	B, D	—
8142Z / 2, 8142Z / 3, 8142Z / 4, 8142Z / 5, 8142Z / 6, 8142Z / 7, 8142Z / 8, 8142Z / 9, 8142Z / 10, 8142Z / 11, 8142Z / 12, 8142Z / 2 OB, 8142Z / 3 OB, 8142Z / 4 OB, 8142Z / 5 OB, 8142Z / 6 OB, 8142Z / 7 OB, 8142Z / 8 OB, 8142Z / 9 OB, 8142Z / 10 OB, 8142Z / 11 OB, 8142Z / 12 OB	26-14	Cu	2	2.0	300	15(1)	B, D	—
8142Z / 2 RF, 8142Z / 3 RF, 8142Z / 4 RF, 8142Z / 5 RF, 8142Z / 6 RF, 8142Z / 7 RF, 8142Z / 8 RF, 8142Z / 9 RF, 8142Z / 10 RF, 8142Z / 11 RF, 8142Z / 12 RF, 8142Z / 2 RF OB, 8142Z / 3 RF OB, 8142Z / 4 RF OB, 8142Z / 5 RF OB, 8142Z / 6 RF OB, 8142Z / 7 RF OB, 8142Z / 8 RF OB, 8142Z / 9 RF OB,8142Z / 10 RF OB, 8142Z / 11 RF OB, 8142Z / 12 RF OB	26-14	Cu	2	2.0	300	15(1)	B, D	—
Note: (1) 10A max. for 300V general industrial use (limited VA).								
Z5.550.4225.0, Z5.550.4325.0, Z5.550.4425.0, Z5.550.4525.0, Z5.550.4625.0,Z5.550.4725.0, Z5.550.4825.0, Z5.550.4925.0, Z5.550.5025.0, Z5.550.5125.0,Z5.550.5225.0	N/A	Cu	1	N/A	300	10(1)	B	—
99.287.0220.0, 99.285.0220.0, 99.063.0220.0, 99.062.0220.0	—	—	1	—	300	12.5	B, D	2 (105)
8142Z/xx PR ##, where "xx" is 2 thru 20	20-14Sol/Str,2 x 20-16Sol/Str	Cu	2	4.43	300	3	B,D#	2(105), 4

8142Z/xx PR HC ##, where "xx" is 2 thru 20	20-14Sol/Str,2 x 20-16Sol/Str	Cu	2	4.43	300	10	B,D#	2(105), 4
8142Z/, 8142Z/..OB, 8142Z/..RF, 8142Z/..RFOB (###)	20-14Sol/Str,2 x 20-16Sol/Str	Cu	2	3.54/0.4	300	1.5	B,D#	2(105), 4
Note: # - These limited ratings are applicable to a terminal block for use in or with industrial control equipment whereby the load on any single circuit of the terminal block does not exceed 15 A at 51-150 V, 10 A at 151-300 V, or 5 A at 301-600 V, or the maximum ampere rating, whichever is less.								
Note: ## - Terminal block series 8142Z/xx PR and 8142Z/xx PR HC can be used as one wire per pole under wire range 20AWG - 14AWG Sol/Str and or two wires per pole under wire range 20AWG - 16AWG Sol/Str.								
Note: ### - Terminal block series 8142Z/, 8142Z/..OB, 8142Z/..RF, 8142Z/..RFOB can be used with one or two wires per pole under wire range 20AWG - 14AWG or 20AWG-16AWG respectively, Sol/Str.								
WRT 6	22-8 sol/str	Cu	2	14	600	50	B,C	2(105), 4
WRT 6 TK	22-8 sol/str	Cu	1	14	600	35	B, C	2(105), 4
	22-10sol/str	Cu	2	14	600	30	B, C	2(105), 4
WT 2.5, may be followed by BLUE	26-12 sol/str	Cu	2	0.4 Nm	600	20	C	2(115),4
WT 2.5 PE	26-12 sol/str	Cu	2	0.4 Nm	—	—	C	2(115),4
WT 4, may be followed by BLUE, D1/2, D1/2 BLUE, D2/2, D2/2 BLUE, E, EVB, TKM or TKM BLUE	26-10 sol/str	Cu	2	0.5 Nm	600	30	C	2(115),4
WT 4, may be followed by PE, D1/2/PE, D2/2/PE or E/PE	26-10 sol/str	Cu	2	0.5 Nm	—	—	C	2(115),4
WT 6, may be followed by BLUE	24-8 sol/str	Cu	2	1.2 Nm	600	50	C	2(115),4
WT 6 PE	24-8 sol/str	Cu	2	1.2 Nm	—	—	C	2(115),4
WT 10, may be followed by BLUE	20-6 sol/str	Cu	2	1.2 Nm	600	65	C	2(115),4
WT 10 PE	20-6 sol/str	Cu	2	1.2 Nm	—	—	C	2(115),4
WT 16, may be followed by BLUE	12-4 sol/str 16-14 sol only	Cu	2	2.0 Nm	600	85	C	2(115),4
WT 16 PE	12-4 sol/str 16-14 sol only	Cu	2	2.0 Nm	—	—	C	2(115),4

Cat. No.	Suitable Conductors kcmil/AWG		OverCurrent Protection Fuse Required Class/Max Amp Rating						SCCR, RMS Sym, kA	Volts Max
	Line	Load	J	T	RK1	RK5	G	CC		
WK 2.5/U/V0	12-14	12-14	100	100	—	—	60	30	100	600
WK 4/U/V0, WK 4 D1/2/U/V0, WK 4 D2/2/U/V0	10-14	10-14	200	200	200	100	60	30	100	600
WK 6/U/V0	8-14	8-14	200	200	200	100	60	30	100	600

WKN 10/U/V0	6-14	6-14	200	200	200	100	60	30	100	600
WKN 16/U/V0	4-12	4-12	200	200	200	100	60	30	100	600
WKN 35/U/V0	2-10	2-10	400	400	400	200	60	30	100	600
WKN 35/U/V0 with jumper bar Cat. No. IVB WKN 35-2	2-10	2-10	400	400	400	200	60	30	100	600
WKN 70/U/V0	2/0-6	2/0-6	400	400	400	200	60	30	100	600
WKN 150/U/V0	350-2/0	350-2/0	400	400	400	200	—	—	100	600
WKFN 2.5/35, WKFN 2.5 D1/2/35, WKFN 2.5 D2/2/35	12-14	12-14	100	100	—	—	60	30	100	600
WKFN 4/35, WKFN 4 D1/2/35, WKFN 4 D2/2/35	10-14	10-14	200	200	200	100	60	30	100	600
WKFN 6/35, WKFN 6 D1/2/35	8-14	8-14	200	200	200	100	60	30	100	600
WKFN 10/35, WKFN 10 D1/2/35	6-14	6-14	200	200	200	100	60	30	100	600
WKFN 16/35, WKFN 16 D1/2/35	4-14	4-14	200	200	200	100	60	30	100	600

Cat. No.	Suitable Conductors kcmil/AWG		OverCurrent ProtectionSelf-Protected Combination Motor Controller, Type E, Required			SCCR, RMS Sym, kA	Volts Max
	Line	Load	Mfr	Type	Max Amp		
WK 2.5/U/V0	12-14	12-14	Siemens	3RV1031-4EA10	32	65	480
WK 4/U/V0	10	10	Siemens	3RV1031-4FA10	40	65	480
WK 4 D1/2/U/V0, WK 4 D2/2/U/V0	10	10	Siemens	3RV1031-4EA10	32	65	480
WK 4 E/U, WK 4 E/U/VB	10	10	Siemens	3RV1021-4CA10	22	50	480
WK 4 E/U, WK 4 E/U/VB	10	10	Siemens	3RV1031-4FA10	40	65	480
WK 6/U/V0	8	8	Siemens	3RV1031-4HA10	50	65	480
WKN 10/U/V0	6	6	Siemens	3RV1041-4KA10	75	65	480
WKN 16/U/V0	4-12	4-12	Siemens	3RV1041-4LA10	90	65	480
WKFN 2.5/35, WKFN 2.5 D1/2/35, WKFN 2.5 D2/2/35	12-14	12-14	Siemens	3RV1021-4BA10	20	65	480
WKFN 4/35, WKFN 4 D1/2/35, WKFN 4 D2/2/35	10	10	Siemens	3RV1031-4EA10	32	65	480
WKFN 6/35, WKFN 6 D1/2/35	8	8	Siemens	3RV1031-4HA10	50	65	480
WKFN 10/35, WKFN 10 D1/2/35	6	6	Siemens	3RV1041-4JA10	63	65	480
WKFN 16/35, WKFN 16 D1/2/35	4-12	4-12	Siemens	3RV1041-4LA10	90	65	480

Cat. No.	Suitable Conductors kcmil/AWG		OverCurrent Protection CirCuit Breaker Required			SCCR, RMS Sym, kA	Volts Max
	Line	Load	Mfr	Type	Max Amp		
WKFN 2.5/35,WKFN 2.5 D1/2/35, WKFN 2.5 D2/2/35	12	12	Siemens	3RV1821-4BD10	20	25	480
WKFN 2.5/35,WKFN 2.5 D1/2/35, WKFN 2.5 D2/2/35	14	14	Siemens	3RV1721-4BD10	20	25	480
WK 2.5/U/V0	12-14	12-14	Siemens	3RV1742-5ED10	32	25	480
WK 4/U/V0	10	10	Siemens	3RV1742-5FD10	35	35	480

WK 4 D1/2/U/V0, WK 4 D2/2/U/V0	10	10	Siemens	3RV1742-5ED10	30	35	480
WKFN 4/35, WKFN 4 D1/2/35, WKFN 4 D2/2/35	10	10	Siemens	3RV1742-5ED10	30	35	480
WK 6/U/V0	8	8	Siemens	3RV1742-5JD10	50	35	480
WKFN 6/35, WKFN 6 D1/2/35	8	8	Siemens	3RV1742-5JD10	50	25	480
WKN 10/U/V0	6	6	Siemens	3RV1742-5PD10	65	25	480
WKFN 10/35, WKFN 10 D1/2/35	6	6	Siemens	3RV1742-5LD10	60	25	480

Cat. No.	Suitable Conductors kcmil/AWG		OverCurrent Protection Fuse Required Class/Max Amp Rating						SCCR, RMS Sym, kA	Volts Max
	Line	Load	J	T	RK1	RK5	G	CC		
WKF 1.5/35	14 Cu	14 Cu	60	60	—	—	30	30	100	300
WKF 1.5 SL/35	14 Cu	14 Cu	60	60	—	—	30	30	100	N/A
WKF 1.5 D1/2/35	14 Cu	14 Cu	60	60	—	—	30	30	100	300
WKF 1.5 D1/2SL/35	14 Cu	14 Cu	60	60	—	—	30	30	100	N/A
WKF 1.5 D2/2/35	14 Cu	14 Cu	60	60	—	—	30	30	100	300
WKF 1.5 D2/2SL/35	14 Cu	14 Cu	60	60	—	—	30	30	100	N/A
WKF 1.5 E2/35	14 Cu	14 Cu	60	60	—	—	30	30	100	300
WKF 1.5 E/SL/35	14 Cu	14 Cu	60	60	—	—	30	30	100	N/A
WKF 35/35	14-2 Cu	14-2 Cu	200	200	100	30	60	30	100	600
WKF 35 SL/35	14-2 Cu	14-2 Cu	200	200	100	30	60	30	100	N/A

(*)- Terminal blocks have been subjected to a 30 min seCureness test as part of the mechanical sequence outlined in UL486 E

(**) Solid wire only

(*2) Devices provided with optional electronic cirCuits have not been evaluated with respect to the suitability of the optional electronic cirCuitry.

#1 These models have been evaluated for it's suitability as protective conductor terminal blocks and complies with the applicable grounding requirements for terminals for use in a protective cirCuit. (commercial and industrial applications).

- Unique Conditions of Acceptability are indicated in the individual Recognition reports.

Marking: Company name or tradename "Wieland" or trademarks , and type, series or catalog designation (type or catalog designation may appear on shipping carton).

Last Updated on 2013-11-14

Questions? Print this page Terms of Use Page Top

© 2014 UL LLC

When the UL Leaf Mark is on the product, or when the word "Environment" is included in the UL Mark, please search the UL Environment database for additional information regarding this product's certification.

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2014 UL LLC".